

Patch Antenna

Large Band - FME-F

Rev. 29/09/2006

Order Code : 4408000004

This antenna is designed to be stuck on an installation and must be put only on a non-metallic surface. The radiation is ensured towards the patch side of the antenna.

Its connection allows to be directly connected on the **Gen 44i / GenSmi** modems.

Type	Patch Antenna – AG250
Frequencies	Large Band - 750Mhz to 2,4GHz - WSVR : <1.15/1
Impedance	50 Ohms
Gain	0 dB on the whole band
Assembly	Self-adhesive (Glass mount) on non metallic surface
Weight	About 160 g
Dimensions	110 x 58mm / thickness max: 10mm
Sort of cable	RG58
Cable Length	2.5 m
Connector	FME-Female

Options :

- **SMA-M / FME-M Adapter** (Order Code: **4405000012**)
necessary to connect to **FASTRACK / GenLoc 31e** modems
- **FME-F / FME-F Antenna extension**
(Order Code: **44090000x0**) x = 1 or 2 or 5 meters
- + **FME-M / FME-M Adapter** (Order Code: **4405000011**)



ERCO & GENER SA may at any time and without notice make changes and improvements to the products and services offered